

INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification Scheme for Explosive Atmospheres

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.:

IECEx TUN 10.0003X

Issue No: 1

Certificate history:

Status:

Current

Issue No. 1 (2019-08-27) Issue No. 0 (2010-07-07)

Date of Issue:

2019-08-27

Page 1 of 4

Applicant:

FAFNIR GmbH

Schnackenburgallee 149 c

22525 Hamburg

Germany

Equipment:

Safety barrier type SB 1 and SB 3

Optional accessory:

Type of Protection:

Intrinsic Safety "i", Flameproof Enclosure "d", Enclosure "t"

Marking:

SB 1: Ex db [ia Ga] IIC T6...T4 Gb resp. Ex ta [ia Da] IIIC T115 °C Da

SB 3: [Ex ia Ga] IIC resp. [Ex ia Da] IIIC

Approved for issue on behalf of the IECEx

Certification Body:

Christian Roder

Position:

Head of the IECEx Certification Body

Signature:

(for printed version)

Date:

2019-08-27

- 1. This certificate and schedule may only be reproduced in full.
- 2. This certificate is not transferable and remains the property of the issuing body.
- 3. The Status and authenticity of this certificate may be verified by visiting the Official IECEx Website.

Certificate issued by:

TÜV NORD CERT GmbH Hanover Office Am TÜV 1, 30519 Hannover Germany





Certificate No: IECEx TUN 10.0003X Issue No: 1

Date of Issue: 2019-08-27 Page 2 of 4

Manufacturer: FAFNIR GmbH

Schnackenburgallee 149 c

22525 Hamburg **Germany**

Additional Manufacturing location(s):

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended.

STANDARDS:

The apparatus and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards:

IEC 60079-0 : 2017 Explosive atmospheres - Part 0: Equipment - General requirements

Edition:7.0

IEC 60079-1: 2014-06 Explosive atmospheres - Part 1: Equipment protection by flameproof enclosures "d"

Edition:7.0

IEC 60079-11: 2011 Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"

Edition:6.0

IEC 60079-31 : 2013 Explosive atmospheres - Part 31: Equipment dust ignition protection by enclosure "t"

Edition:2

This Certificate **does not** indicate compliance with electrical safety and performance requirements other than those expressly included in the Standards listed above.

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in

Test Report:

DE/TUN/ExTR10.0005/00 DE/TUN/ExTR10.0005/01

Quality Assessment Report:

DE/TUN/QAR06.0013/06



Certificate No:	IECEx TUN 10.0003X	Issue No: 1
Date of Issue:	2019-08-27	Page 3 of 4
	Schedule	
EQUIPMENT: Equipment and systems covered by	y this certificate are as follows:	
The safety barrier type SB 1 is preferintrinsically safe sensors (two-wire) to	rably used in conjunction with a certified flameproof enclosure on non-intrinsically safe circuits.	e, e. g. HPH Ex d, for the connection of
The safety barrier type SB 3 is used	to connect intrinsically safe sensors (four-wire) to non-intrinsi	ically safe circuits.
See attachment for technical data.		
SPECIFIC CONDITIONS OF USE:	YES as shown below:	
1. The side of the safety barrier SB 1	, where the encapsulation can be seen, must be operated pr	otected against UV light.
	minal compartment. It must be installed in an enclosure that zone 1 in conjunction with a flameproof enclosure (such as h	
3. Repair of flameproof joints of SB 1	is not planned.	
bonding must exist for the entire intri	tion must be connected to the equipotential bonding of the ponsically safe area). Therefore, the safety barriers do not mee intrinsically safe circuit, the device must therefore be discont	t the dielectric strength requirements. When
5. The maximum permissible pressu	re of SB 1 is 30 bar.	



Certificate No:	IECEx TUN 10.0003X	Issue No: 1
-----------------	--------------------	-------------

Date of Issue: 2019-08-27 Page 4 of 4

DETAILS OF CERTIFICATE CHANGES (for issues 1 and above):

The changes affect the addition of the new type SB 3 and the dust explosion protection.

Furthermore, the equipment was assessed according to the latest standards. Further the address was changed.

Annex

Attachment to IECEx TUN 10.0003X Issue 1.pdf

TÜV NORD CERT GmbH Hanover Office Am TÜV 1 30519 Hannover Germany



Page 1 of 1 Attachment to IECEx TUN 10.0003X Issue 1

Temperatures

The ambient temperature range for type **SB 3** is -40 °C to +70 °C.

The ambient temperature range for type **SB 1** is

Used as Category 2G equipment

Ambient temperature			
-40 °C to +40 °C			
-40 °C to +55 °C			
-40 °C to +85 °C			
-40 °C to +85 °C			
-40 °C to +85 °C			
-40 °C to +85 °C			

Used as Category 1D equipment

	Maximum surfa	Ambient temperature	
	dust layer ≤ 5 mm	Immersed in dust	Ambient temperature
Ī	+115 °C	+115 °C	-40 °C to +85 °C

Electrical data

Type SB 1

Supply circuit $U = 24 V_{DC}$

 $U_m = 253 V$

Output circuit in type of protection "Intrinsic Safety" Ex ia IIC/IIB/IIIC

Maximum values: U_o = 28.4 V

 $I_o = 100 \text{ mA}$ $P_i = 705 \text{ mW}$

Characteristic line: linear

Maximum permissible outer capacitance and inductance:

	Ex ia IIC		Ex ia IIB/IIIC	
Lo	500 μH	560 μH	5 mH	2 mH
Co	71 nF	68 nF	330 nF	400 nF

Type SB 3

Supply circuit $U = 24 V_{DC}$ for channel 1

 $U = 5 V_{DC}$ for channel 2 and 3

 $U_{\rm m} = 253 \, {\rm V}$

Output circuit in type of protection "Intrinsic Safety" Ex ia IIC/IIB/IIIC

Maximum values: $U_o = 28.4 \text{ V}$

 I_o = 95 mA P_i = 507 mW

Characteristic line: linear

Maximum permissible outer capacitance and inductance:

The state of the s				
	Ex ia IIC		Ex ia IIB/IIIC	
Lo	500 µH	200 µH	5 mH	2 mH
Co	72 nF	79 nF	340 nF	410 nF